



This product is currently under revision in order to meet new CE Mark requirements. Please contact Tempcon Sales Office for alternatives, or product advice

### S-UCC-M001 and S-UCC-M006 Pulse Input Adapters

The Electronic Switch Pulse Input Adapter connects sensors with pulse outputs to loggers with smart-sensor inputs. This Smart Sensor is compatible with electronic switch closures such as FET or open-collector outputs, or CMOS-level logic signals with a maximum input frequency of 120 Hz (120 pulses per second).

#### Specification:

**Maximum Input Frequency:** 120 Hz (120 pulses per second)

**Measurement Range:** 0 – 65,533 pulses per logging interval

**Resolution:** 1 pulse

**Lockout time:** 45  $\mu$ s  $\pm$  10%

**Recommended Input Type:** Electronic solid state switch closure or CMOS-level digital output (example: FET, opto-FET or open collector)

**Preferred Switch State:** Active low input Normally open

**Edge Detection:** Falling edge, Schmitt Trigger buffer (logic levels: low  $\leq$  0.6 V, high  $\geq$  2.7 V)

**Minimum Pulse Width:** 1 ms

**Input/Output Impedance:** 100 K $\Omega$

**Open Circuit Input Voltage:** 3.3 V

**Maximum Input Voltage:** 3.6 V

**User Connection:** 24 AWG wires, 2 leads: white(+), black(-)

**Operating Temperature Range:** -40° to 75°C (-40° to 167°F)

**Overall Cable Length:** 1 m (3.3 ft.)

**Housing:** Weatherproof PVC housing protects input adapter electronics

**Housing Dimensions:** 14 x 0.95 cm (5.5 x 0.375 in.)

**Weight:** 310 g (11 oz.)

**Bits per Sample:** 16

**Number of Data Channels:** 1

**Measurement Averaging Option:** No (reports the number of pulses over the logging interval)

#### Order Information:

#### Part No:

Electronic Switch Pulse Input Adapter  
(1 Metre Cable)

S-UCC-M001

Electronic Switch Pulse Input Adapter  
(6 Metre Cable)

S-UCC-M006